

**SPECIFICATIONS** LED Replacement is approximately 1/2 of the CFL wattages. Adapter will add .25" - .50" to overall length

	PART #	FIXTURE SOCKET	LAMP TYPE	RATING	DESCRIPTION
	Adapter-1	E12	Medium (E26)	125v/0.8A	E12 > Medium
	Adapter-1A	Candelabra (E11)	Medium (E26)	125v/0.8A	E11 > Medium
	Adapter-2	Intermediate (E17)	Candelabra (E12)	250v/4A	Intermediate > Candelabra
	Adapter-3	Intermediate (E17)	Medium (E26)	125v/0.8A	Intermediate > Medium
	Adapter-4	Double Contact (Bayonette)	Medium (E26)	125v/0.8A	Double Bayonetta > Medium
	Adapter-5	Medium (E26) Extender	Medium (E26)	250v/4A	Medium > Medium (Extender), adds 1.25" to length
	Adapter-6	Medium (E26)	Mogul (E39)	250v/4A	Medium > Mogul
	Adapter-7	Mogul (E39)	Medium (E26)	250v/4A	Mogul > Medium
	Adapter-8	Mogul (E39) No Extra Length	Medium (E26)	250v/4A	Mogul > Medium, no extra length
	Adapter-9	Mogul (E39) Extender	Mogul (E39)	660v/6A	Mogul > Mogul (Extender), adds 1.25" to length
	Adapter-10	GU24	Medium (E26)	250v/6A	GU24 > Medium
	Adapter-11	G24D (1/2/3)	Medium (E26)	250v/2.5A	G24D (1/2/3) > Medium
	Adapter-12	G24Q (1/2/3) GX24Q (1/2/3/4/5)	Medium (E26)	250v/2.5A	G24Q (1/2/3) > Medium, also replaces GX24Q (1/2/3/4/5)
	Adapter-13	GX23 (1/2/3)	Medium (E26)	250v/2.5A	GX23 (1/2/3) > Medium
	Adapter-14	GX23 Medium	Medium (E26)	250v/2.5A	G23 (1/2/3) > Medium
	Adapter-15	Mogul (EX39) Pulse Start	Mogul (E39)	250v/4A	Pulse Start Mogul > Mogul
	Adapter-16	Medium (E26) Extender	Medium (E26)	250v/0.8A	Medium > Medium (Extender) for 4 K.V. pulse rated socket, adds 1.25" to length
	Adapter-17	Double Contact (Sox)	Mogul (E39)	250v/0.8A	Double contact (Sox) > Mogul
	Adapter-18	Medium (E26)	Candelabra (E12)	250v/0.8A	Medium > Candelabra
	Adapter-19	Medium (E26) Extender	Medium (E26)	250v/4A	Medium > Medium (Extender), adds 2.50" to length

Specifications and actual product may vary.